

DESCRIPTION

The AN-9001 is an electret condenser microphone designed for ambient noise detection. It is used in conjunction with the AN-001T Ambient Noise Sensor Input module in the 9000 Series system. It can be mounted in a 1-gang electrical box in the ceiling or wall.

SPECIFICATIONS

Type	Electret condenser microphone
Phantom Power	14 - 26 V DC
Current Consumption	7 mA (at 24 V DC)
Directivity	Omnidirectional (hemispherical)
Impedance	200 Ω
Rated Sensitivity	-5 dB (1 kHz, 0 dB = 1 V/Pa)
Frequency Response	100 Hz - 10 kHz
Output Terminal	Removable terminal block (3 pins)
Operating Temperature	-10 °C to +40 °C
Finish	Panel: ABS resin, white Frame, Case: Surface-treated steel plate
Dimensions	$\phi 130 \times 37$ (D) mm
Weight	200 g
Accessory	Removable terminal plug (3 pins) ...1, Box mounting screw (No.6-32UNC $\times$ 30) ...2, Box mounting screw (M4 $\times$ 30) ...2
Option	9000 series plug-in module: AN-001T

APPEARANCE

Note: Since no electrical box is supplied with the unit, prepare it separately.

